## Concord

## OPTIX RECESSED 1250x310 2L 4000K ALU SSC **2023690**



## **Features**

• OPTIX RECESSED 1250x310 2L 4000K ALU SSC is a high efficacy low glare luminaire for office and education applications. Ceiling recessed 1250x310 mm. Aluminised plastic extra low glare optics in 2 lines configuration. White RAL9016 fixture body. SylSmart Standalone capable. 4000K Neutral White LED, CRI>80, chromaticity tolerance of 3-step MacAdam ellipse. Luminous flux 3600lm. Power consumption 27W. Luminaire efficacy 133lm/W. Lifespan: 48,500 hours L90B10. UGR<16, Luminance at 65°<200 Cd/m2, IK07, IP20. Photobiological safety risk gro...

## CIBSE TM66

Result			
Category	Points Scored	Maximum possible points	Assessment
Product design	76	134.0	2.3
Manufacturing	23.4	46.5	2
Materials	7	24.0	1.2
Ecosystem	21	43.0	2
Overall performance	127.4	247.5	1.88

/ery poor circular economy performance
Some circular economy functionality
Definite/substantial progress to circularity
Excellent circularity
-

Technical Memorandum (TM) 66 describes a Circular Economy's main aims, how it can be achieved and what it's practice will mean to the different branches of our industry like specifiers, manufacturers, contractors, and Facilities Managers.

The Circular Economy Assement Method for Manufacturing (CEAM-Make)'s list of 66 searching questions, the majority of which askfor back-up evidence, is split into four sections:

Product Design: Covering topics such as design for long life and repair Manufacturing: Additive and subtractive techniques and localisation Usage of recyclable materials rather than virgin

Ecosystem : Repair or upgrade services to complement circular economy design

The outcome of the assement is a single figure rating by which product comparisons can be made. A TM66 score demonstrates a product's performance in the context of a Circular Economy

CIBSE (2021) Circular Economy Assessment Method - Make TM66 Digital Tool beta version 22nd October 2021 (London: Chartered Institution of Building Services Engineers)

