SYLVANIA

Resisto 1200 HE IP66 DALI 2800LM 840 EM 0010280



Features

• Resisto, integrated LED weatherproof luminaire, with UV stabilized flat diffuser designed to achieve uniform lit appearance, optimise light output and to reduce glare. 301 stainless steel diffuser clips and fixing brackets for surface mounting. Polycarbonate housing and diffuser - no yellow discolouration over time. 2800lm; 22W; 127lm/W; 4000K; SDCM<3; DALI dimmable; CRI80; IP66; IK08; Class I; 69,000hrs (L80B20) lifespan; 1200mm x 89mm x 88mm; D-mark; 3-hour maintained emergency batteries.

CIBSE TM66

Result						
Category	Points Scored	Maximum possible points	Assessment		How to analyse the score	
Product design	63.0	134.0	1.9	0.0 to 0.5	Very poor circular economy perform	
Manufacturing	19.2	46.5	1.7	0.5 to 1.5	Some circular economy functionality	
Materials	5.0	24.0	0.8	1.5 to 2.5	Definite/substantial progress to circu	
Ecosystem	17.0	43.0	1.6	2.5 to 4.0	Excellent circularity	
Overall performance	104.2	247.5	1.50			

Technical Memorandum (TM) 66 describes a Circular Economy's main aims, how it can be achieved and what it's practice will mean to the different branches of our industry like specifiers, manufacturers, contractors, and Facilities Managers.

The Circular Economy Assement Method for Manufacturing (CEAM-Make)'s list of 66 searching questions, the majority of which askfor back-up evidence, is split into four sections :

Product Design :Covering topics such as design for long life and repairManufacturing :Additive and subtractive techniques and localisationMaterials :Usage of recyclable materials rather than virginEcosystem :Repair or upgrade services to complement circular economy design

The outcome of the assement is a single figure rating by which product comparisons can be made. A TM66 score demonstrates a product's performance in the context of a Circular Economy

CIBSE (2021) Circular Economy Assessment Method - Make TM66 Digital Tool beta version 22nd October 2021 (London : Chartered Institution of Building Services Engineers)

Light your world